

BoB ASSISTANT®

Predictive maintenance assistant



BoB ASSISTANT makes a thorough analysis of the vibration signature of an industrial piece of equipment, ensuring its remote condition monitoring. The data is transmitted via a public or private LoRaWAN® radio frequency network.

APPLICATIONS

- Supervision of industrial installations equipped with motors (pumps, ventilation, cooling unit, ...)
- Optimization of maintenance operations

BENEFITS & FEATURES

- LoRaWAN®, Class A
- Easy to install and use
- ~4 years of autonomy
- Measuring ranges / accuracies:
 - Vibration: 0-400Hz/± 3Hz and 0-12.4kHz/± 100Hz
 - Temperature: -20°C to +50°C / ± 1°C

CERTIFICATION

- RED, UKCA, RoHS

BoB ASSISTANT® monitors the vibration signature of a piece of equipment (pump, ventilation, etc...). After a learning period of 7 days, the sensor alerts in case of vibration drift, allowing maintenance teams to intervene before a breakage or failure. Data transmission over the LoRaWAN® network is done periodically or immediately in case of alert:

- Exceeding the vibration drift threshold (adjustable)
- Machine on/off (adjustable)

Installation and commissioning are quick and easy.

The sensor is equipped with:

- A button for activation and deactivation,
- An RGB LED to monitor configuration and pairing to the network,
- 2 magnets to ease the installation of the sensor on the equipment (also possible by gluing, riveting, screwing...).

THE LARGEST IOT PRODUCTS RANGE FOR YOUR PROJECT

WATTECO is a European leader in the design and manufacture of smart IoT devices to suit all remote reading and data collection solutions.

WATTECO is a LoRa Alliance® member.



Each sensor is identified by a QR code on the label.

The data pre-processed by the on-board artificial intelligence is gathered in a report transmitted over the LoRaWAN® network every 180 minutes.

The sensor periodically reports the machine's operating time over the last 180 minutes, the rate of vibration drift recorded over this period, the battery level, the temperature, and a predictive failure probability.

Machine status alerts (Start/Stop) are also available (can be inhibited by Downlink command).

Powered by a 3.6V/2000mAh battery, the autonomy of the sensor is more than 4 years with a configuration of 8 transmissions per day.

Machine vibration knowledge is stored in flash, and applied back when the device is restarted, or battery is replaced.

Machine vibration knowledge and battery values can be reset either through the HMI interface or network Downlink command.

TECHNICAL DATA

RADIOFREQUENCY		Frequency (MHz)	Transmit Power (dBm)	Receiver Sensitivity (dBm)		
EU: 863 - 870			+14	-140		
FIRMWARE						
Protocol		LoRaWAN®, Class A				
Activation method		Over-The-Air Activation (OTAA)				
Data encryption		AES128				
Sampling period		10 minutes (configurable)				
Transmission cycles		Every 180 minutes				
MEASUREMENTS		Vibrations		Temperature		
Range		Low frequency: 0 - 400Hz High frequency: 0 - 12800Hz		-20°C to +50°C		
Accuracy		± 3,125Hz (0 - 400Hz) ± 100Hz (0 - 12800Hz)		± 1°C		
ALARMS						
Vibration		Vibration drift of 25% by default (configurable as Downlink at 10, 15 or 20%)				
Status		Switching on / off (status frames can be inhibited by downlink control)				
POWER SUPPLY						
Voltage		3.6V / 2000mAh – Replaceable lithium battery Transmitted battery voltage level in remaining percentage				
Autonomy (in a range of +10°C to +25°C)		> 4 years: sampling every 10 minutes and 8 transmissions per day				
USER INTERFACE						
QR Code		Product code, serial number, batch number				
Push button + RGB LED		Configuration, network pairing and sensor status				
ENCLOSURE	Size (mm)	Weight (g)	Fastenings	IP rating	Material	Fire resistance
	76 x 79 x 23	75	Supplied with 2x magnets and nuts	IP68	ABS	UL94-HB
ENVIRONMENT						
Operation		-20°C / +50°C ; +0% rH / +95% rH (non-condensing)				
Storage		10°C / +30 °C ; +0% rH / +60% rH				
STANDARDS & REGULATIONS						
Radio Equipment Directive 2014/53/EU, ROHS					UK	CE

PRODUCT NUMBER

REFERENCE	HS Code	MODEL DESCRIPTION
50-80-011	85 17 62	BoB ASSISTANT - LoRaWAN® EU868
71-80-015		BATTERY REPLACEMENT KIT